

High Voltage 8-CH LED Driver

General Description

The RT8576 is an 8-CH LED driver capable of delivering 120mA for each channel. The RT8576 is a current mode boost converter with an adjustable switching frequency via the OSC pin from 100kHz to 1MHz and a wide VIN range from 9V to 28V.

The PWM output voltage loop selects and regulates the LED pin with the highest voltage string to 0.6V, hence allowing voltage mismatches between LED strings. The RT8576 automatically detects and disconnects any unconnected and/or broken strings during operation from PWM loop to prevent V_{OUT} from over voltage.

The 3% matched LED currents on all channels are simply programmed with a resistor. A very high contrast ratio true digital PWM dimming can be achieved by driving the PWM pin with a PWM signal.

When an abnormal situation (open/short/thermal) occurs, a state signal will be sent to the system to shut down the IC.

The RT8576 is available in TSSOP-24 (Exposed Pad) and SOP-24 packages.

Ordering Information

RT8576	□ □
	Package Type
	CP : TSSOP-24 (Exposed Pad)
	S : SOP-24
	Lead Plating System
	G : Green (Halogen Free and Pb Free)

Note :

Richtek products are :

- ▶ RoHS compliant and compatible with the current requirements of IPC/JEDEC J-STD-020.
- ▶ Suitable for use in SnPb or Pb-free soldering processes.

Features


- Wide Input Supply Voltage Range : 9V to 28V
- Adjustable Boost Controller Switching Frequency from 100kHz to 1MHz
- Programmable Channel Current
- Channel Current Matching : $\pm 3\%$
- External Dimming Control
- Boost MOSFET Over Current Protection
- Automatic LED Open/Short Protection to Avoid Output Over Voltage
- VIN Under Voltage Lockout
- Adjustable Over Voltage Protection
- Under Voltage Protection
- Thermal Shutdown Protection
- Abnormal State Indicator for Open/Short/Thermal Condition
- RoHS Compliant and Halogen Free

Applications

- LCD TV, Monitor Display Backlight
- LED Driver Application
- General Purpose Constant Current Source


Marking Information

RT8576GCP



RT8576GCP : Product Number
YMDNN : Date Code


RT8576GS




RT8576GS : Product Number
YMDNN : Date Code

Pin Configurations

(TOP VIEW)



TSSOP-24 (Exposed Pad)



SOP-24

Typical Application Circuit




Figure 1. General Application





Figure 2. External P-MOSFET Isolation Application

Functional Pin Description

Pin No.		Pin Name	Pin Function
TSSOP-24 (Exposed Pad)	SOP-24		
1	1	PWM	Digital Dimming Control. Connect a pull high or pull low resistor from this pin to ground.
2, 3, 4, 5	2, 3, 4, 5	OUT1 to OUT4	Channel 4 to Channel 1 LED Current Sink. Leave the pins unconnected if not used.
6, 25 (Exposed Pad)	6	GND	Ground. The exposed pad must be soldered to a large PCB and connected to GND for maximum power dissipation.
10, 7, 8, 9	15, 8, 9, 7	OUT5 to OUT8	Channel 8 to Channel 5 LED Current Sink. Leave the pins unconnected if not used.
11	10	OVS	Over Voltage and Under Voltage Protection. PWM boost converter turns off when VOVP or VUVP goes higher than 1.2V or lower than 0.6V, respectively.
12	11	ISSET	LED Current Setting Pin. A resistor or a current from DAC on this pin programs the full LED current.
13	12	OSC	Switching Frequency Setting Pin. Connect a resistor between OSC and GND to set the boost converter switching frequency.
14	13	EN	Chip Enable. When EN is pulled low, chip will be in shutdown mode.
15	14	CS	Current Sense Input. During normal operation, this pin senses the voltage across the external inductor current sensing resistor for peak current mode control and is also used to limit the inductor current during every switching cycle.
16	16	EXT	Boost Converter Power Switch Gate Output. This pin drives the external power N-MOSFET device.
17	17	VCCA	1 μ F capacitor should be placed on this pin to stabilize the 5V output of the internal regulator. This regulator is for chip internal use only.
18	18	PGND	Boost Converter Power Ground.
19	19	VIN	Power Supply of the Chip. For good bypass, a low ESR capacitor placed close to the pin is required.
20	20	SS	Soft-Start Pin. Place a capacitor of at least 10nF from this pin to GND to set the soft-start time period.
21, 23	21, 23	NC	No Internal Connection.
22	22	COMP	PWM Boost Converter Loop Compensation Node.
24	24	STATE	Boost Converter Operation State Output.

Function Block Diagram



Absolute Maximum Ratings (Note 1)

Supply Voltage, V_{IN} , STATE	33V
LED1 to LED8	50V
PWM, EN, EXT, CS, SS, COMP, OSC, VCCA, OVS, ISET	5.5V
Power Dissipation, P_D @ $T_A = 25^\circ\text{C}$	
TSSOP-24 (Exposed Pad)	2.500W
SOP-24	1.111W
Package Thermal Resistance (Note 2)	
TSSOP-24 (Exposed Pad), θ_{JA}	40°C/W
TSSOP-24 (Exposed Pad), θ_{JC}	7°C/W
SOP-24, θ_{JA}	90°C/W
Junction Temperature	150°C
Lead Temperature (Soldering, 10 sec.)	260°C
Storage Temperature Range	-65°C to 150°C
ESD Susceptibility (Note 3)	
HBM (Human Body Mode)	2kV
MM (Machine Mode)	200V

Recommended Operating Conditions (Note 4)

Supply Voltage, V_{IN}	9V to 28V
LED1 to LED8	45V
Junction Temperature Range	-40°C to 125°C
Ambient Temperature Range	-40°C to 85°C

Electrical Characteristics

($V_{IN} = 12\text{V}$, $T_A = 25^\circ\text{C}$, unless otherwise specified)

Parameter		Symbol	Test Conditions	Min	Typ	Max	Unit
Supply Voltage							
Supply Current		I _{VIN}	Switching Off	--	5	--	mA
Shutdown Current		I _{SHDN}	V _{EN} < 0.7V	--	--	10	μA
VDD LDO Output		V _{CCA}		--	5	--	V
VDD LDO Capability		I _{VCCA}		30	--	--	mA
VIN UVLO Threshold		V _{UVLO}	VIN Rising	--	--	8	V
			Hysteresis	--	1.4	--	
EN Input Threshold Voltage	Logic-High	V _{ENH}		1.5	--	--	V
	Logic-Low	V _{ENL}		--	--	0.8	
LED Current Programming							
LED Current Accuracy			R _{ISET} = 4.53kΩ, V _{PWM} > 1.2V	114	120	126	mA
LED Current Matching			R _{ISET} = 4.53kΩ, V _{PWM} > 1.2V $\frac{I_{(MAX)} - I_{(MIN)}}{2 \times I_{(Avg)}} \times 100\%$	--	1.5	3	%
LED1 to LED8 Regulation Voltage			I _{LED} = 120mA	--	0.6	--	V

To be continued

Parameter		Symbol	Test Conditions	Min	Typ	Max	Unit
V _{LED} Threshold			No Connection	--	0.1	--	V
ISET Pin Voltage				--	1.2	--	V
Dimming							
PWM Input Threshold Voltage	Logic-High	V _{PWMH}		1.2	--	--	V
	Logic-Low	V _{PWML}		--	--	0.4	
PWM Boost Controller							
Switching Frequency	f _{OSC}	R _{OSC} = 24kΩ		--	1	--	MHz
		R _{OSC} = Open		--	100	--	kHz
Minimum On Time	t _{ON}			--	100	--	ns
Maximum Duty Cycle	D _{max}			80	--	--	%
CS Current Sense Limit		Input Current Limit		--	0.5	--	V
Gate Driver Source				--	2.5	--	A
Gate Driver Sink				--	3	--	A
OVP, UVP, SCP, OTP and Soft-Start							
OVP Threshold	V _{OVP}			1.1	1.2	1.3	V
UVP Threshold	V _{UVP}			0.57	0.6	0.63	V
SCP Threshold	V _{SCP}	LED1 to LED8		--	4.3	--	V
Soft-Start Current	I _{SS}	V _{SS} < 2.5V		--	6	--	μA
Thermal Shutdown Temperature	T _{SD}	Lockout Temperature Point		--	150	--	°C
Thermal Shutdown Hysteresis	ΔT _{SD}	Resume Temperature Point		--	20	--	°C
STATE Low Voltage	V _{STATE}	Open Drain at 10mA		--	--	0.5	V

Note 1. Stresses listed as the above “Absolute Maximum Ratings” may cause permanent damage to the device. These are for stress ratings. Functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may remain possibility to affect device reliability.


Note 2. For TSSOP-24 (Exposed Pad), θ_{JA} is measured in natural convection at T_A = 25 $^{\circ}$ C on a high-effective thermal conductivity test board of JEDEC 51-7 thermal measurement standard. For SOP-24 θ_{JA} is measured in natural convection at T_A = 25 $^{\circ}$ C on a low-effective thermal conductivity test board of JEDEC 51-3 thermal measurement standard. The measurement case position of θ_{JC} is on the exposed pad of the package.

Note 3. Devices are ESD sensitive. Handling precaution is recommended.


Note 4. The device is not guaranteed to function outside its operating conditions.

Typical Operating Characteristics


LED Current vs. Input Voltage




LED Current vs. PWM Duty Cycle




Efficiency vs. Input Voltage




Power On from V_{IN}



Power On from VEN



Power On from PWM



Application information

The RT8576 is an 8-CH driver controller that delivers well matched LED current to each channel of LED strings. The external N-MOSFET current source will accommodate the power dissipation difference among channels resulting from the forward voltage difference between the LED strings. With high speed current source N-MOSFET drivers, the RT8576 features highly accurate current matching, while also providing very fast turn-on and turn-off times. This allows a very narrow minimum on or off pulse. The RT8576 integrates adjustable switching frequency and soft-start and provides circuitry for over temperature, over voltage, under voltage and current limit protection.

Soft-Start

The RT8576 employs a soft-start feature to limit the inrush current. The soft-start circuit prevents excessive inrush current and input voltage droop. The soft-start time is determined by a capacitor, C_{SS} , connected between SS and GND and charged with a 6 μ A constant current as shown in the following equation.

$$t_{SS}(\text{max}) = C_{SS} \times 4 \times 10^5 (\text{s})$$

The value of capacitor C_{SS} is user-defined to satisfy the designer's requirement.

Compensation

The regulator loop can be compensated by adjusting the external components connected to the COMP pin. The COMP pin is the output of the internal error amplifier. The compensation capacitor will adjust the zero to maintain stability and the resistor value will adjust the compensator gain for fast transient response. Typical values of the compensation components are $R_C = 560\Omega$, $C_C = 0.22\mu\text{F}$.

LED Connection

The RT8576 equips 8-CH LED drivers and each channel supports up to 15 LEDs. The LED strings are connected from the output of the boost converter to pin OUTx (x = 1 to 8) respectively. If one of the LED channel is not in use, the OUTx pin should be opened directly.

Setting and Regulation of LED current

The LED current can be calculated by the following equation :

$$I_{LED} \cong \frac{543.6}{R_{ISET}}$$

where R_{ISET} is the resistor between the ISET pin and GND. This setting is the reference for the LED current at pin OUTx and represents the sensed LED current for each string. The DC/DC converter regulates the LED current according to the setting.

Over Voltage and Under Voltage Protection

The RT8576 integrates Over Voltage Protection (OVP) and Under Voltage Protection (UVP). When the voltage at the OVS pin rises above the threshold voltage of approximately 1.2V or falls below the threshold voltage of approximately 0.6V, the internal switch will be turned off and the STATE pin will be pulled high. The internal switch will be turned on again once the voltage at the OVS pin returns to normal range. The output voltage can be clamped at a certain voltage level and can be calculated by the following equations :

$$V_{OUT(OVP)} = V_{OVP} \times \left(1 + \frac{R_{OVP2}}{R_{OVP1}} \right)$$

$$V_{OUT(UVP)} = V_{UVP} \times \left(1 + \frac{R_{OVP2}}{R_{OVP1}} \right)$$

where R_{OVP1} and R_{OVP2} are the resistors in the resistive voltage divider connected to the OVS pin. If at least one string is in normal operation, the controller will automatically ignore the open strings and continue to regulate the current for the strings in normal operation. Suggested value for R_{OVP2} is up to 3M Ω to prevent loading effect.

LED Short Circuit Protection

The RT8576 integrates LED Short Circuit Protection (SCP). If one of the OUT1 to OUT8 pin voltages exceeds a threshold of approximately 4.3V during normal operation, the STATE pin will be pulled high for a fault signal.

STATE

After the IC is enabled. STATE will output logic high if LED short/OVP/UVP/OTP conditions exist. STATE will be reset after V_{IN} or EN is re-applied.

Setting the Switching Frequency

The RT8576 switching frequency is programmable from 100kHz to 1MHz by adjusting the oscillator resistor, R_{OSC} . The switching frequency can be calculated by the following equation :

$$f_{SW} \cong 100k + \frac{21.6 \times 10^9}{R_{OSC}}$$

Current Limit Protection

The RT8576 can sense the R_{SENSE} voltage between the CS pin and GND to achieve over current protection. The boost converter senses the inductor current during the on period. The duty cycle depends on the current signal and internal slope compensation compared with the error signal. The external switch will be turned off when the current signal is larger than the internal slope compensation. In the off period, the inductor current will decrease until the internal switch is turned on by the oscillator. The current limit value can be calculated by the following equation :

$$\text{Current Limit (A)} \cong \frac{0.5V}{R_{SENSE}}$$

Brightness Control

The RT8576 features a digital dimming control scheme. A very high contrast ratio true digital PWM dimming is achieved by driving the PWM pin with a PWM signal. The recommended PWM frequency is 200Hz to 10kHz, but the LED current cannot be 100% proportional to duty cycle, especially for high frequency and low duty ratio.

Over Temperature Protection

The RT8576 has over temperature protection function to prevent the IC from overheating due to excessive power dissipation. The IC will shut down and the STATE pin will be pulled high when junction temperature exceeds 150°C. Main converter starts switching after junction temperature cools down by approximately 20°C.

Inductor Selection

The value of the inductance, L, can be approximated by the following equation, where the transition is from Discontinuous Conduction Mode (DCM) to Continuous Conduction Mode (CCM) :

$$L = \frac{D \times (1-D)^2 \times V_{OUT}}{2 \times f \times I_{OUT}}$$

The duty cycle can be calculated as the following equation :

$$D = \frac{V_{OUT} - V_{IN}}{V_{OUT}}$$

where V_{OUT} is the maximum output voltage, V_{IN} is the minimum input voltage, f is the operating frequency, and I_{OUT} is the sum of current from all LED strings.

The boost converter operates in DCM over the entire input voltage range when the inductor value is less than this value, L. With an inductance greater than L, the converter operates in CCM at the minimum input voltage and may be discontinuous at higher voltages.

The inductor must be selected with a saturated current rating that is greater than the peak current as provided by the following equation :

$$I_{PEAK} = \frac{V_{OUT} \times I_{OUT}}{\eta \times V_{IN}} + \frac{V_{IN} \times D \times T}{2 \times L}$$

where η is the efficiency of the power converter.

Diode Selection

Schottky diodes are recommended for most applications because of their fast recovery time and low forward voltage. Power dissipation, reverse voltage rating, and pulsating peak current are important parameters for consideration when making a Schottky diode selection. Make sure that the diode's peak current rating exceeds I_{PEAK} and reverse voltage rating exceeds the maximum output voltage.

Capacitor Selection

The input capacitor reduces current spikes from the input supply and minimizes noise injection to the converter. For general applications, six to eight 4.7μF ceramic capacitors are sufficient. A value higher or lower may be used depending on the noise level from the input supply and the input current to the converter.

It is recommended to choose a ceramic capacitor based on the output voltage ripple requirements. The minimum value of the output capacitor, C_{OUT} , can be calculated by the following equation :

$$C_{OUT} = \frac{I_{OUT} \times D}{\Delta V_{OUT} \times f}$$

where ΔV_{OUT} is the peak-to-peak ripple voltage at the output.

Thermal Considerations

For continuous operation, do not exceed absolute maximum junction temperature. The maximum power dissipation depends on the thermal resistance of the IC package, PCB layout, rate of surrounding airflow, and difference between junction and ambient temperature. The maximum power dissipation can be calculated by the following formula :

$$P_{D(MAX)} = (T_{J(MAX)} - T_A) / \theta_{JA}$$

where $T_{J(MAX)}$ is the maximum junction temperature, T_A is the ambient temperature, and θ_{JA} is the junction to ambient thermal resistance.

For recommended operating condition specifications of the RT8576, the maximum junction temperature is 125°C and T_A is the ambient temperature. The junction to ambient thermal resistance, θ_{JA} , is layout dependent. For TSSOP-24 (Exposed Pad) packages, the thermal resistance, θ_{JA} , is 40°C/W on a standard JEDEC 51-7 four-layer thermal test board. For SOP-24 packages, the thermal resistance, θ_{JA} , is 90°C/W on a standard JEDEC 51-3 single-layer thermal test board. The maximum power dissipation at $T_A = 25^\circ\text{C}$ can be calculated by the following formula :

$$P_{D(MAX)} = (125^\circ\text{C} - 25^\circ\text{C}) / (40^\circ\text{C/W}) = 2.500\text{W for}$$

TSSOP-24 (Exposed Pad) package

$$P_{D(MAX)} = (125^\circ\text{C} - 25^\circ\text{C}) / (90^\circ\text{C/W}) = 1.111\text{W for}$$

SOP-24 package

The maximum power dissipation depends on the operating ambient temperature for fixed $T_{J(MAX)}$ and thermal resistance, θ_{JA} . For the RT8576 packages, the derating curves in Figure 3 allow the designer to see the effect of rising ambient temperature on the maximum power dissipation.




Figure 3. Derating Curve for RT8576 Packages

Layout Considerations

Careful PCB layout is very important for designing switching power converter circuits. The following layout guidelines should be strictly followed for best performance of the RT8576.

- ▶ The power components L1, D1, C_{IN} , C_{OUT} must be placed as close as possible to the IC to reduce current loop. The PCB trace between power components must be as short and wide as possible.
- ▶ The compensation circuit should be kept away from the power loops and shielded with a ground trace to prevent any noise coupling. Place the compensation components, R_C and C_C , as close as possible to pin 22.
- ▶ The exposed pad of the chip should be connected to ground plane for thermal consideration.




Figure 4. TSSOP-24 (Exposed Pad) PCB Layout Guide






Figure 5. SOP-24 PCB Layout Guide

Outline Dimension



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	1.000	1.200	0.039	0.047
A1	0.000	0.150	0.000	0.006
A2	0.800	1.050	0.031	0.041
b	0.190	0.300	0.007	0.012
D	7.700	7.900	0.303	0.311
e	0.65		0.026	
E	6.300	6.500	0.248	0.256
E1	4.300	4.500	0.169	0.177
L	0.450	0.750	0.018	0.030
U	3.700	4.900	0.146	0.193
V	2.200	3.100	0.087	0.122

24-Lead TSSOP (Exposed Pad) Plastic Package



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	15.189	15.596	0.598	0.614
B	7.391	7.595	0.291	0.299
C	2.362	2.642	0.093	0.104
D	0.330	0.508	0.013	0.020
F	1.194	1.346	0.047	0.053
H	0.229	0.330	0.009	0.013
I	0.102	0.305	0.004	0.012
J	10.008	10.643	0.394	0.419
M	0.381	1.270	0.015	0.050

24-Lead SOP Plastic Package

Richtek Technology Corporation

Headquarter

5F, No. 20, Taiyuen Street, Chupei City

Hsinchu, Taiwan, R.O.C.

Tel: (8863)5526789 Fax: (8863)5526611

Richtek Technology Corporation

Taipei Office (Marketing)

5F, No. 95, Minchiuan Road, Hsintien City

Taipei County, Taiwan, R.O.C.

Tel: (8862)86672399 Fax: (8862)86672377

Email: marketing@richtek.com

Information that is provided by Richtek Technology Corporation is believed to be accurate and reliable. Richtek reserves the right to make any change in circuit design, specification or other related things if necessary without notice at any time. No third party intellectual property infringement of the applications should be guaranteed by users when integrating Richtek products into any application. No legal responsibility for any said applications is assumed by Richtek.